

PANEL DISPLAY SCREEN USER GUIDE



Version 1
PL-INSTL-PANELDISELAY-EN



www.proloncontrols.com
1-877-977-6566
info@proloncontrols.com
17510 Rue Charles, Suite 100, Mirabel, QC, J7J 1X9



Table of Contents

Launching Proton Focus.....	3
Connecting to a Project	3
Locking a Project.....	5
Addressing a VC2000 Controller.....	7
Enabling Limited Access	8
Discovering Controllers on the Network.....	10
Adding Controllers Using "Get List"	12
Configuring a Controller	13
Changing Zone Temperature Setpoint.....	16
Overriding Parameters	17
Unpinning the Screen.....	18
Changing the Tablet Time	18
Changing the Language	20
Changing the Units.....	22
Connecting to a Google Account.....	24




Launching Prolon Focus




1. The display will power up once power is applied to the control cabinet. *(If not powered up, hold the button on the bottom right of the device.)* Look for the Prolon Focus icon. Tap on the Prolon Focus icon to launch the app.

Connecting to a Project


Note that the Prolon Focus App will automatically connect to the controller. However, occasionally, a connection must be established manually.




1. Tap on "Local Project"



2. Tap on the top right connection icon.




3. Tap on "USB".



4. The icons will be colored red/green/blue upon a successful connection.




Locking a Project




To prevent unwanted access, a user may lock the project. A password must be entered to access the project.


1. From the local page, hold the "Local Project" icon.




2. Tap on "Get Information".



3. Tap on "Lock Project".




4. Enter the password of your choice.
(8 characters minimum)




5. To finish the setup, tap on "Save".



Addressing a VC2000 Controller



1. It is possible to address the VC2000 zone controllers directly from the display. From the System page, tap on the configuration icon.




2. Tap on "Assign VC2000 Addresses".




Enabling Limited Access

To prevent unwanted configuration changes to a system, enable limited access to the project. A user with limited access can view all the controller icons & visuals. They can access & change the following settings:


- scheduling
- zone temperature (occupied & unoccupied setpoints)




1. From the local page, hold the "Local Project" icon.




2. Tap on "Get information".



3. Tap "Enable Limited Access".




4. Enter the desired password. Tap on "Activate" when done.




5. Tap "Save".




Discovering Controllers on the Network




1. On the Local project page, tap on the Configuration Icon in the top right.




2. Tap "Discover All".



3. Tap "OK" when prompted to do so.



4. The Network Controller will scan every address on the network and add all discovered controllers to the project. Each follower device will also automatically be sorted under its respective master controller (if applicable).




5. Once the operation is complete, tap "OK". You can now see the entire project connected to this Network Controller.




Adding Controllers Using "Get List"

The "Get List" function can only be used to retrieve the list of controllers that operate under a Master Controller.



1. Tap on the "System" with the Master Controller you want to retrieve the list from.




2. Hold the controller's icon. A drop down menu will appear. Tap on "Get List".

Note: The discovery and Get list functions are similar but present the following differences:


- Discovery: Discovers all Master and Follower controllers and sorts them.
- Get List: Discovers ONLY followers under a specific Master controller.




Configuring a Controller




1. Tap on the system icon that has the controller you want to configure.




2. Tap on the configuration icon




3. Tap on the top right configure button.




4. Scroll down to access the menus and tap on the desired menu.




5. Tap on a setting that you want to change.



6. Enter the new value and tap "OK".




7. Return to the main menu page.




8. Tap on the "Save" icon to apply the changes.




Changing Zone Temperature Setpoint



1. Tap on the zone controller you wish to access.




2. Scroll down and tap on "Setpoints" icon.




3. Adjust the setpoint to the desired value.
4. Tap "Save" in the right upper corner when done.




Overriding Parameters



1. From the controller's home page. Scroll down to the desired output you wish & to override.




2. Enable the override by sliding the override slider icon.



3. Tap on the value box and set the desired parameter's value.




Unpinning the Screen




1. Upon start-up of the Focus app, the user can choose whether or not to pin the app (a pinned app cannot be exited without unpinning it). To unpin the app, hold the ◀ and the ■ icons at the same time to unpin the Focus App and return to normal navigating mode of the display.

Changing the Tablet Time


When a Prolon tablet is shipped, it is set to Eastern Time Zone. If the display lacks an internet connection, it will retain this time zone setting. Please ensure to adjust the display to the current time manually.




1. Tap the home screen icon to access the tablet's main page. Look for the settings icon and tap on it.



2. Scroll down to "Date and time" and tap on it.



3. Make sure the "Automatic date & time" slider is off. Tap on "Select time zone".




4. Scroll up or down to the appropriate time zone and select the time by tapping on it.




Changing the Language


To change the language in the Focus app, the language of the operating system of the tablet must be changed. The Proton Focus app will match the tablet's language (English or French are offered).




1. Tap the home screen icon to access the display's main page. Look for the settings icon and tap on it.



2. Scroll down to "Language & input" and tap on it.



3. Tap on "Language".




4. Scroll down to the language you want to use and tap on it.




Changing the Units


By default, the Focus app comes with the Temperature Units set in Fahrenheit. It is possible to change the units through the settings of the app.




1. On the main page of the app, tap on the settings icon.



2. Tap on "Units".



3. Tap on the desired units.




4. Tap "Save".




Connecting to a Google Account


In the event an update of the Focus app is required, a Google Account must be associated with the tablet.




1. From the home screen go to "Settings".



2. Tap on "Accounts".



3. Tap on "Add an account"



4. You can now enter your Google account informations.

For more information on the controllers operating on the Prolon Network or on Focus capabilities. Please refer to www.proloncontrols.com.

VER. 1

PL-INSTL-PANELDISPLAY-EN

© Copyright 2024 Prolon. All rights reserved.

No part of this document may be photocopied or reproduced by any means, or translated to another language without prior written consent of Prolon. All specifications are nominal and may change as design improvements are introduced. Prolon shall not be liable for damages resulting from misapplication or misuse of its products. All trademarks are the property of their respective owners.